

AMENDMENTS TO THE CLAIMS

The following listing of claims will replace all prior versions and listings of claims in the application.

1. (Previously Presented) A clock converter for synchronizing the phase of a phase locked loop (PLL) feedback signal output from voltage controlled oscillating means with the phase of an input signal using phase detector means, to output a clock signal of a predetermined frequency, comprising:

voltage controlled oscillating means for outputting a positive feedback signal for a positive feedback loop, the voltage controlled oscillating means including:

a first buffer forming a portion of the positive feedback loop that outputs the positive feedback signal from one output terminal of the first buffer, which uses voltage controlled phase shifting means, and that outputs the PLL feedback signal from another output terminal of the first buffer; and

a second buffer that outputs the clock signal.

2. (Previously Presented) The clock converter according to Claim 1, wherein at least one of the first buffer and the second buffer further comprises an ECL (emitter coupled logic) differential amplifying circuit.

3. (Currently Amended) The clock converter according to Claim 1, wherein:

the PLL feedback signal output from the first buffer is fed back to the phase detector means through signal transmitting means for adjusting impedance; and further comprising feedback frequency dividing means for dividing the frequency of the PLL feedback signal.

4. (Previously Presented) The clock converter according to Claim 3, wherein:

in the signal transmitting means, the PLL feedback signal supplied from the first buffer is supplied to a first connection point between a first resistor and a second resistor among first to third resistors connected in series between a power source and a ground;

a second connection point between the second resistor and third resistor is connected to the ground through a first capacitor;

the first connection point is connected to a first input terminal of a differential ECL amplifier in the feedback frequency dividing means; and

the second connection point is connected to a second input terminal of the differential ECL amplifier in the feedback frequency dividing means.

5. (Previously Presented) The clock converter according to Claim 3, wherein:

in the signal transmitting means, the PLL feedback signal supplied from the first buffer is supplied to a first connection point between the first resistor and the second resistor among first to third resistors connected in series between a power source and a ground through a second capacitor;

a second connection point between the second resistor and third resistor is connected to the ground through a first capacitor;

the first connection point is connected to a first input terminal of a differential CMOS amplifier in the feedback frequency dividing means; and

the second connection point is connected to a second input terminal of the differential CMOS amplifier in the feedback frequency dividing means.

6. (Original) The clock converter according to Claim 4, wherein, when the resistance value of the second resistor is R_M , and the resistance values of the first and the third resistors connected to both ends of the second resistor are R_H and R_L , respectively, then $R_H \gg R_M$ and $R_L \gg R_M$.

7. (Previously Presented) The clock converter according to Claim 4, wherein an output terminal of the differential amplifying circuit forming the first buffer is connected to a termination resistor with a resistance value larger than that of the output impedance of the differential amplifying circuit.

8. (Cancelled)

9. (Cancelled)

10. (Cancelled)

11. (Cancelled)

12. (Original) The clock converter according to Claim 5, wherein, when the resistance value of the second resistor is R_M , and the resistance values of the first and the third resistors connected to both ends of the second resistor are R_H and R_L , respectively, then $R_H \gg R_M$ and $R_L \gg R_M$.

13. (Cancelled)

14. (Cancelled)

15. (Cancelled)

16. (New) A clock converter for synchronizing the phase of a phase locked loop (PLL) feedback signal output from voltage controlled oscillating means with the phase of an input signal using phase detector means, to output a clock signal of a predetermined frequency, comprising:

voltage controlled oscillating means for outputting a positive feedback signal for a positive feedback loop, the voltage controlled oscillating means including:

a first buffer forming a portion of the positive feedback loop that outputs the positive feedback signal from one output terminal of the first buffer, which uses voltage controlled phase shifting means, and that outputs the PLL feedback signal from another output terminal of the first buffer; and

a second buffer that outputs the clock signal; and

feedback frequency dividing means for dividing the frequency of the PLL feedback signal, wherein:

the PLL feedback signal output from the first buffer is fed back to the phase detector means through signal transmitting means for adjusting impedance;

in the signal transmitting means, the PLL feedback signal supplied from the first buffer is supplied to a first connection point between a first resistor and a second resistor among first to third resistors connected in series between a power source and a ground;

a second connection point between the second resistor and third resistor is connected to the ground through a first capacitor;

the first connection point is connected to a first input terminal of a differential ECL amplifier in the feedback frequency dividing means; and

the second connection point is connected to a second input terminal of the differential ECL amplifier in the feedback frequency dividing means.

17. (New) A clock converter for synchronizing the phase of a phase locked loop (PLL) feedback signal output from voltage controlled oscillating means with the phase of an input signal using phase detector means, to output a clock signal of a predetermined frequency, comprising:

voltage controlled oscillating means for outputting a positive feedback signal for a positive feedback loop, the voltage controlled oscillating means including:

a first buffer forming a portion of the positive feedback loop that outputs the positive feedback signal from one output terminal of the first buffer, which uses voltage controlled phase shifting means, and that outputs the PLL feedback signal from another output terminal of the first buffer; and

a second buffer that outputs the clock signal; and

feedback frequency dividing means for dividing the frequency of the PLL feedback signal, wherein:

the PLL feedback signal output from the first buffer is fed back to the phase detector means through signal transmitting means for adjusting impedance;

in the signal transmitting means, the PLL feedback signal supplied from the first buffer is supplied to a first connection point between the first resistor and the second resistor among first to third resistors connected in series between a power source and a ground through a second capacitor;

a second connection point between the second resistor and third resistor is connected to the ground through a first capacitor;

the first connection point is connected to a first input terminal of a differential CMOS amplifier in the feedback frequency dividing means; and

the second connection point is connected to a second input terminal of the differential CMOS amplifier in the feedback frequency dividing means.